



PA-M1WP

Order No.: 0179300

PRODUCTINFOS

Wall module,

for local insertion of audio signals to PA matrix mixing amplifier PA-M224 or PA-M412.

- Intended application: volume control of 1 zone, local insertion of audio signals
- 2 x RCA jack for line signals
- Microphone connection via 3-pole XLR jack
- 14 V phantom power
- Volume control
- Signal selector button with LED indication which allows a priority circuit of locally inserted audio signals (MIC or LINE) in the respective zone
- Connection to PA-M224 or PA-M412 and power supply via RJ45 jack and Cat. 5 network cable (copper, supplied w/o cable), cable length up to 200 m
- Matching flush-mounted housing ATT-300C is available at option

Manufacturer information:

MONACOR INTERNATIONAL GmbH & Co. KG

Konsul-Smidt-Str. 68

28217 Bremen

Germany
info@monacor.com

Safety and warning notices

Only use the device indoors and protect it from dripping and splashing water, high humidity and heat (permissible operating temperature range 0 - 40 °C).

Do not operate the appliance if there is visible damage to the appliance, if a defect is suspected after a fall or similar, or if malfunctions occur. Always return the appliance to a specialised workshop for repair.

If the appliance is to be taken out of service permanently, hand it over to a local recycling centre for environmentally friendly disposal.

TECHNICAL SPECIFICATIONS

PA-M1WP

Description	wall module
Type	remote control of 1 zone
Colour	white
Material	plastic
Suitable for	PA-M224, PA-M412
Power supply	via PA-M224, PA-M412
Dimensions	80 x 80 x 50 mm
Weight	90 g
Connections	1 x XLR (microphone), 1 x RCA L/R (line), 1 x RJ45
Other features	14 V phantom power
Packing unit	1
Packaging dimensions (W x H x L)	0.09 x 0.09 x 0.085 m
Gross weight	0.135 kg
Net weight	0.09 kg

PA-M1WP

EAN code	4007754273380
Net weight	0.09 kg