



FGA-40MF

Order No.: 0213050

PRODUCTINFOS

Ground isolator,

compact design, for preventing signal interference and hum loops which may occur, e.g. when connecting PC sound cards or laptops to an amplifier.

- Galvanically isolated inputs and outputs
- 2 RCA jacks
- 2 RCA plugs
- Input/output impedance: 20 k Ω
- Frequency range: 20-30,000 Hz
- THD: < 0.01%
- Transmission ratio 1:1
- Ø 24 mm x 38 mm, 32 g
- Length including connection cable: approx. 40 cm

www.musicnstuff.de 07/2014

“There are many little helpers available for studio, stage and home stereo systems. With the FGA-40MF, the product range from MONACOR includes a special transformer for unbalanced stereo line signals which is an easy-to-use aid of compact size for the protection against ground loops. And, does it work? Of course, it

does. This device prevents any hum noise previously heard when using a standard cable with stereo RCA connectors in both directions. Oh, by the way: in addition to models with RCA plugs and RCA jacks, MONACOR also offers them with plugs only or with mini connectors for computers or MP3 players.”

Manufacturer information:

MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

Safety Notes and Warning Messages

The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).

If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

TECHNICAL SPECIFICATIONS

FGA-40MF

Description	ground isolator
Frequency range	20-30,000 Hz
Input impedance	20 kΩ
Output impedance	20 kΩ
Transmission ratio	1:1
THD	< 0.01%
Admiss. ambient temp.	0-40 °C
Dimensions	Ø 24 mm x 38 mm
Weight	32 g
Inputs	1 x RCA plug L/R, 1 x RCA inline jack L/R
Outputs	1 x RCA plug L/R, 1 x RCA inline jack L/R

FGA-40MF

EAN code	4007754228359
Net weight	0.037 kg